

HAMMOND®

XPk-100

MIDI PEDALBOARD


O
O
XK-2



The Hammond ProLine® division are proud to introduce the XPK-100 Pedalboard. Simply plug it in, connect it to your keyboard via MIDI, and you're ready to enhance your playing with bass lines provided by your foot, leaving your hands free to play melody and accompaniment. And, when used in conjunction with Hammond's XK-2 and XB-1 Drawbar Keyboards, the XPK-100 allows you to create a "virtual B-3."


HAMMOND XPK-100

MIDI Pedalboard



Unique MIDI setup:

- In addition to a MIDI OUT port, the XPK-100 features two separate MIDI IN ports, thus allowing the easy use of two MIDI keyboards (see illustration). An ideal twin-manual MIDI system!



- Ideal for use with the Hammond XM-1 Drawbar Module and the XB-1 and XK-2 Drawbar Keyboards. Also suitable for use with a great variety of MIDI-compatible keyboards (for more information, contact your Hammond dealer).

SPECIFICATIONS

- 13-note pedalboard, fixed velocity
- LED display: 7 segments, 3 characters
- Panel Switches: PLAY/EDIT, PRESET/EDIT Plus and Minus, TRANSPOSE/LOCK, CONTROL
- Jacks: DC power input, MIDI IN 1, MIDI IN 2, MIDI OUT
- Accessories: AC power supply, MIDI cable
- Weight: 8.5kg
- Dimensions: W56cm D39cm H13cm

EDIT Parameter List

Advanced Features	Values
*E00 PK MIDI Channel	1 > 16
*E01 Transpose	-5 > +6
*E02 Octave	-1 > +4
*E03 Poly/Mono Mode	Poly/Mono
*E04 PK Hold ON/OFF	ON/OFF
*E05 PK Volume	1 > 127
*E06 Fixed Vel. Value	1 > 127
*E07 Control Channel	1 > 16, Pedal
*E08 CONTROL Sw.Func.	36 Selectable functions (Leslie Slow/Fast, Sustain, etc.)
*E09 CONTROL Sw.Mode	Alternate/Momentary
*E10 Program Change	OFF, 1 > 128
*E11 Bank Select MSB	0 > 127
*E12 Bank Select LSB	0 > 127
E13 System	Preset Reset, MIDI Merge ON/OFF, MIDI Data Dump
*Data can be saved to a Preset.	

For details please contact:

SUZUKI MUSICAL INST.MFG.CO.,LTD.
Hamamatsu, Japan